QIPE
NOV 19 2003
JC48
PATENT & TRADEMARK OFFICE

Image

Mail Stop Patent
Attorney Docket No. 82531

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Application of:

Idan KASPIT et al.

Serial No. 10/681,249

Filed: October 9, 2003

For: **TWO STAGE OPTICAL AMPLIFIER**

TRANSMITTAL LETTER

Commissioner for Patents
P.O. Box 1450
Alexandria, VA 22313-1450

Sir:

Submitted herewith for filing in the U.S. Patent and Trademark Office is the following:

(1) Transmittal Letter;
(2) Request for Priority Under 35 U.S.C. § 119; and
(3) Priority Document Application No. IL 152193.

Please charge any required fee, or credit any overpayment, in connection with this matter to deposit Account No. 14-0112.

Respectfully submitted,

NATH & ASSOCIATES

By: Harold L. Novick
Registration No. 26,011
Customer No. 20529

Date: November 19, 2003

NATH & ASSOCIATES PLLC
1050 15th Street N.W., Suite 600
Washington, D.C. 20005
HLN/be

PTO/SB/21 (09-04)
Approved for use through 07/31/2006. OMB 0651-0031
U.S. Patent and Trademark Office: U.S. DEPARTMENT OF COMMERCE

PTO
NOV 19 2003
PATENT & TRADEMARK OFFICE
JC48

Mail Stop Patent
Attorney Docket No. 82531

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Application of

Idan KASPIT

Serial No. 10/681,249

Filed: October 9, 2003

For: **TWO STAGE OPTICAL AMPLIFIER**

CLAIM FOR PRIORITY UNDER 35 U.S.C. §119

Commissioner for Patents
P.O. Box 1450
Alexandria, VA 22313-1450

Sir:

In the matter of the above-captioned application, notice is hereby given that the Applicant claims as priority date October 9, 2002, the filing date of the corresponding application filed in ISRAEL, bearing Application Number 152193.

A Certified Copy of the corresponding application is submitted herewith.

Respectfully submitted,

Date: November 19, 2003

By: _____
Harold L. Novick
Registration No. 26,011
Customer No. 20529

NATH & ASSOCIATES PLLC
1030 Fifteenth Street N.W.
Sixth Floor
Washington, D.C. 20005
(202) 775-8383

HLN/be

מדינת ישראל
STATE OF ISRAEL

Ministry of Justice
Patent Office

משרד המשפטים
לשכת הפטנטים

This is to certify that annexed hereto is a true copy of the documents as originally deposited with the patent application of which particulars are specified on the first page of the annex.

זאת לתעודה כי רצופים בזה העתקים נכונים של המסמכים שהופקדו לכתחילה עם הבקשה לפטנט לפי הפרטים הרשומים בעמוד הראשון של הנספח.

04 NOV 2003

This היום

Commissioner of Patents
רשם הפטנטים

נתאשר
Certified

חוק הפטנטים, תשכ"ז - 1967
PATENTS LAW, 5727-1967

בקשה לפטנט
Application for Patent

לשימוש הלשכה
For Office Use

מספר: Number
152193

תאריך: Date
הוקדם / נדחה
Ante / Post-dated
09 -10- 2002

אני, (שם המבקש, מענו - ולגבי גוף מאוגד - מקום התאגדותו)
I, (Name and address of applicant, and, in case of a body corporate, place of incorporation)

לייטסקייפ נטוורקס בע"מ
חברה ישראלית
רחוב הסיבים 30
פתח תקווה 49517
ישראל

Lightscape Networks Ltd.
An Israeli company
30 Hasivim Street
Petach Tikva 49517
Israel

בעל אמצאה מכח Owner, by virtue of הדין Right of Law

ששמה הוא: of an invention the title of which is:

(בעברית) (Hebrew)
מגבר אופטי דו-דרגי

(באנגלית) (English)
Two Stage Optical Amplifier

מבקש בזאת כי ינתן לי עליה פטנט. Hereby apply for a patent to be granted to me in respect thereof

• בקשת חלוקה Application for Division	• בקשת פטנט מוסף - Application for Patent of Addition	• דרישת דין קדימה Priority Claim		
מבקשת פטנט from Application	• לבקשה/לפטנט to Patent/Application	מספר/סימן Number/Mark	תאריך Date	מדינת האיגוד Convention Country
מס' No. _____ מיום dated _____	מס' No. _____ מיום dated _____			
• יפוי כח: כללי/ P.O.A.: general/specific - attached/to be filed later הוגש בענין Has been filed in case פ. 141632				
המען למסירת הודעות ומסמכים בישראל Address for Service in Israel ד"ר גיל אינגל אי. סי. איי טלקום בע"מ רח' הסיבים 30 פתח תקווה 49517 ECIP/F027/IL				
חתימת המבקש Signature of Applicant Helena Levin		היום 9th בחודש Oct. שנת 2002		
				לשימוש הלשכה For Office Use

טופס זה, כשהוא מוטבע בחותם לשכת הפטנטים ומושלם במספר ובתאריך ההגשה, הינו אישור להגשת הבקשה שפרטיה רשומים לעיל.
This form, impressed with the Seal of the Patent Office and indicating the number and date of filing, certifies the filing of the application, the particulars of which are set out above.

• מחק את המיותר Delete whatever is inapplicable

מגבר אופטי דו-דרגי

Two Stage Optical Amplifier

לייטסקייפ נטוורקס בע"מ

Lightscape Networks Ltd.

ECIP/F027/IL

Two stage optical amplifier

Field of the invention

The present invention concerns a configuration of a so-called two stage optical amplifier which is a widely known element in optical telecommunication networks.

Background of the invention

Traditionally, a two-stage optical amplifier serves as a piece of equipment of an optical line.

Usually, the two stages of amplification are two different amplifying units connected in sequence in a pre-manufactured assembly, where the first unit is considered the first stage of the assembly and called an optical pre-amplifier, while the second unit (an optical booster) which follows the first one is considered the second stage. Such a configuration is usually implemented as a unidirectional integral assembly and, in the frame of the present description, will be called a conventional two-stage unidirectional configuration.

Each of the amplifying units usually comprises a single stage optical amplifier such as EDFA (Erbium Doped Fiber Amplifier) characterized by particular optical features (gain, flatness, noise, output power, etc).

The conventional two-stage unidirectional configuration is advantageous in that it has a higher maximum output power than a single stage optical amplifier and allows using relatively inexpensive amplifying units which might have differing optical parameters. However, when connecting such amplifiers into the two-stage configuration, degradation

may appear in the flatness of the gain over the band of optical wavelengths supported by the combined amplifier. That's why the two amplifiers for the two-stage configuration are usually selected to have gain characteristics which allow compensating one another. The gain flatness can be adjusted by an operator during the manufacturing process, when interconnecting between the two stages. In practice, when manufacturing the assembly, the optical parameters of the first stage and the second stage of the unidirectional configuration are matched to produce the best performance, using a control interconnection between the two stages, that control interconnection comprising a communication channel and a micro controller, both provided within the assembly and serving the two mentioned stages of the unidirectional assembly. During operation of the assembly, the control interconnection continues fulfilling its functions for matching parameters of the amplifiers and coordinates their operation.

The unidirectional configuration may include a network element connected between the two stages (in the mid-stage); by now, such intermediate elements have been used for signal attenuation, dispersion compensation, etc.

One example of such a configuration is described in US 6,215,584.

It should be mentioned, that the conventional two-stage or multi stage unidirectional assembly, even when allowing independent control of parameters of the stages by the control circuit, is arranged in such a way that if a fiber cut occurs before the first stage amplifier, it behaves as a single integral device i.e., all stages of the assembly are shut down by the assembly controller, since the whole assembly appears to be useless in the absence of the input optical signal. Such a feature contradicts to inserting OADM (Optical Add Drop Multiplexer) in the mid-stage of the above-

described configuration. One should recall that OADM is intended for receiving a WDM (wavelength division multiplexed) multi-channel optical signal, dropping at least part of optical information channels, and/or adding information to at least one of vacant optical channels for further transmitting a newly composed multi-channel multiplexed optical signal. Therefore, OADM in the mid-stage seems to be useless, since the complete shutdown of the two-stage configuration in the case of a fiber cut is harmful not only to the information received at the 1st stage, but also to the information added by the OADM.

The unidirectional two-stage configuration could theoretically be built from two separate amplifiers, which do not form an integrated assembly and thus each of the stages works independently when the other stage fails for any reason. Such a configuration would easily allow inserting OADM or any other element in the mid stage. However, in that case, high quality amplifiers with flat optical characteristics would be required and the configuration would become too expensive.

Object of the invention

It is the object of the present invention to provide a two-stage optical amplifier configuration which would be suitable for inserting, between the two stages thereof, any network element (including optical add drop multiplexer OADM) and being free from disadvantages of the known two-stage configurations of optical amplifiers.

Summary of the invention

According to the first aspect of the invention, the Inventors propose a two-stage configuration of an optical amplifier wherein each stage of the configuration is formed by at least one optical amplifying unit, the configuration:

being adapted for inserting in a mid-stage thereof any network element (possibly comprising OADM),

allowing matching at least one optical characteristics of the two stages, and

being capable of leaving one of the stages to function in a regular regime whenever the other of the stages is shut down.

It should be noted that each stage of the two-stage configuration may be composed of one or more amplifying units. In the simplest case, each stage of the configuration comprises one optical amplifier.

The above-defined configuration, while allowing independent functioning of the two stages, can be built from inexpensive amplifying units matched from the point of optical characteristics.

To obtain said at least one matched optical characteristics, it is proposed that the two stages of the two-stage configuration be interconnected with one another by a control-communication channel for, at least, gain control of said amplifying units. Preferably, the channel provides also for control of other optical parameters of the amplifying units (and thus of the resulting optical amplifier), such as gain flatness and gain tilt.

Selection of the parameters to be matched and the preliminary matching of the first stage and the second stage of the configuration are to be performed by the manufacturer. Further, the control-communication

channel serves for adjusting the parameters during operation of the assembly.

According to one embodiment of the configuration, it can be implemented on the conventional integral unidirectional two-stage amplifier's assembly, by providing to it said ability to prevent shutting down the other one of the stages when one of the stages is to be shut down (say, when a fiber cut is detected).

To enable operability of the other stage when one of the stages in the integral unidirectional two-stage amplifying assembly is to be shut down, changes should be introduced in the control-communication channel of the assembly (for example, in its micro-controller). The control-communication channel (or control interconnection), which exists in the conventional integral two-stage unidirectional assembly and comprises a communication channel and a micro controller, will enable matching the parameters of the two stages also in the presence of such element as OADM in the mid-stage.

According to one preferred embodiment of the invention, the two-stage configuration comprises its 1st stage and its 2nd stage located at two separate modules (cards), wherein the optical connection and the control-communication channel between the stages is arranged externally between said cards.

In accordance with the most preferred embodiment of the invention, there is provided a combined configuration (which will further be referred to as East-West bi-directional configuration) comprising a pair of two-stage configurations as defined above, for respectively serving two opposite directions of optical transmission; in the combined configuration each of the separate modules accommodates the 1st stage of

one said two-stage configuration and the 2nd stage of the other said two-stage configuration.

Any of the above-mentioned embodiments (i.e., any of the defined two-stage configurations) can be implemented using the following newly proposed universal assembly that forms a second aspect of the present invention:

A universal integrated two-stage optical amplifiers' assembly (*universal assembly*) comprising a 1st stage and a 2nd stage, each formed by at least one optical amplifying unit, said 1st and 2nd stages being preliminarily matched from the point of at least one optical characteristics,

input of the assembly being connected to input of the 1st stage,

output of the 2nd stage being connected to output of the assembly,

output of the 1st stage and input of the 2nd stage are respectively connected to a pair of mid-stage contacts of the assembly (thereby allowing introducing an optical element either between the 1st stage and the 2nd stage of the universal assembly, or between any of the stages of said universal assembly and a complementary stage of another similar universal assembly,

the assembly also comprises a control-communication circuit capable of matching at least one optical characteristics of the assembly and of preventing shut down of one stage when the other is shut down , wherein said circuit being selectively configurable either to form a control-communication channel between the 1st stage and the 2nd stage of said assembly, or to disconnect said channel there-between while enabling each of the 1st stage and the 2nd stage to form a separate control-

communication channel with a complementary stage located on another similar universal assembly.

Preferably, the 1st stage and the 2nd stage are preliminarily matched in such a manner that the 1st stage of the universal assembly is preliminarily adjusted to match to a set of average characteristics designed for the 2nd stage, while the 2nd stage of the universal assembly is preliminarily adjusted to match to a set of average characteristics designed for the 1st stage, so that any of the 1st stage and the 2nd stage of said universal assembly approximately matches to a complementary stage of said universal assembly or of another similar universal assembly.

Also preferably, the control-communication circuit is capable of further dynamically matching any of the 1st stage and the 2nd stage of said universal assembly to a complementary stage of said universal assembly or of another similar universal assembly .

In the preferred embodiment, the control-communication circuit comprises a switch or just a pair of contacts, dividing the circuit into two separate portions respectively suitable for being connected to corresponding separate portions of a control-communication circuit of another similar universal assembly, so to form a control-communication channel between a 1st stage of one assembly and a 2nd stage of the other assembly and wise versa.

The above-defined universal integrated two stage assembly (*universal assembly*) can be used for forming:

a) a unidirectional two-stage configuration based on one universal integrated assembly(when the mid-stage contacts serve for connecting the stages of the same assembly and the control-communication channel is also formed there-between (shown as assembly 20 or 120 in Fig. 3a);

b) a bi-directional configuration (shown in Fig. 3b) where each of the two directions of optical transmission is served by the unidirectional two-stage configuration based on one universal integrated assembly;

c) a unidirectional two-stage configuration based on two different universal assemblies, where 1st stage of one assembly is directly or indirectly connected to 2nd stage of the other assembly, and the control-communication channel is formed between these same stages of the different assemblies (shown as a contour 51 in Fig. 3c or as a contour 60 in Fig. 3d);

d) a bi-directional configuration (Figs. 3c, 3d) based on two different universal assemblies, where each direction of optical transmission is served by the unidirectional configuration (c) . This bi-directional configuration is a so-called East-West configuration.

Owing to the fact that the stages of the two-stage configurations are located at different modules (assemblies, cards), and due to the fact that the control-communication channel is arranged between the two modules to enable matching of the optical parameter(s) of the stages belonging to different modules, the configurations (c) and (d) ensure:

- easy replacement of any of the stages if needed, without a harm to the second stage and,
- upon replacing the module with another universal assembly, operation without degradation of the two-stage configuration performance since the matching will be performed by the newly formed control-communication channel.

All the above-proposed two-stage optical amplifying configurations are suitable for inserting OADM in the mid-stage.

To understand inventiveness of the proposed two-stage optical amplifying configurations and the universal assembly over the prior art, one should recall that:

firstly, a conventional two-stage unidirectional configuration has a set of improved optical characteristics but, when a fiber cut is detected before its first stage amplifier, behaves as an integral device shutting down both its stages;

secondly, OADM, if inserted in the mid-stage of the conventional configuration, would be disabled since the complete shutdown of the two-stage configuration in a case of a fiber cut is harmful to the information added by the OADM; it should be noted that the information introduced by the OADM comes from source(s) non-affected by the fiber cut, and could be independently transmitted to the network if not the complete shut down of the assembly;

thirdly, a two-stage amplifier, if assembled from optical amplifiers being not of the highest quality, needs prior matching there-between and never enables replacement of any of the amplifiers (be it possible) without degradation of the configuration performance, since re-matching the new pair of amplifiers is very problematic.

The proposed configurations and the universal assembly allow overcoming the above-mentioned disadvantages.

According to a slightly different aspect of the invention, there is also provided a system comprising any of the described two-stage optical amplifier configurations, with an OADM in the mid-stage.

Further details and explanations will be given as the description proceeds.

Brief description of the drawings

The invention will be further described and illustrated with the aid of the following non-limiting drawings in which:

Fig. 1a shows a conventional one stage optical amplifier

Fig. 1b shows a conventional two-stage unidirectional optical amplifier assembly

Fig. 2 schematically illustrates the proposed universal two stage optical amplifier assembly suitable for inserting a network element in the mid-stage.

Fig. 3a is a schematic block-diagram illustrating a bi-directional two-stage amplifier configuration where each direction of the transmission is served by one two-stage amplifier assembly.

Fig. 3b illustrates how the configuration shown in Fig. 3a can be built using the universal assemblies as shown in Fig. 2.

Fig. 3c illustrates a schematic block-diagram of a bi-directional two-stage amplifier configuration where each direction of transmission is served by two two-stage amplifier assemblies (East-West configuration).

Fig. 3d shows how the East/West configuration of Fig. 3c can be implemented using a pair of the universal assemblies shown in Fig. 2.

Detailed description of the invention

Fig. 1a (prior art) schematically illustrates a basic optical amplifier 10. Arrows at the input and the output of the amplifier show direction of the optical transmission. Any optical amplifier is characterized by a number of optical parameters, which include, for example, the following set: gain, flatness of the amplifier's gain (as a function of wavelength), noise figure, maximal output power of the amplifier. A stand-alone amplifier of a high quality usually has good optical characteristics (say, the uniform flatness

over a sufficiently wide spectrum of wavelengths), and is relatively expensive.

An amplifying unit of a moderate quality is quite cheap but is not used alone since it has non-uniform optical characteristics.

Fig. 1b (prior art) schematically illustrates a conventional two-stage optical amplifier assembly 12 where the output of a 1st stage amplifying unit 14 is connected to the input of a 2nd stage optical amplifying unit 16 either directly (a dotted line 15) or via an optical element (not shown) which can be connected in the mid-stage.

Owing to the fact that the 1st stage and the 2nd stage amplifiers produce a summary gain and are preliminarily matched in the pre-fabricated assembly, the set of parameters which is provided by the assembly 12 is improved in comparison with that of a single amplifying unit.

The parameters are matched also dynamically, during operation of the assembly, by providing there-between a control-communication channel schematically shown as 13 with a micro controller 17 to ensure the power and gain control. The conventional configuration 12 shuts down completely in case any of the stages 14 or 16 fail or has to be shut down.

According to one embodiment of the present invention, the conventional configuration 12 can be modified into such preventing the complete shut down when one of the stages is shut down. For example, the micro controller 17 can be reprogrammed to prevent shutting down the 2nd stage 16 in case of a fiber cut before the 1st stage 14, while still shutting down the 1st stage 14.

Fig. 2 schematically illustrates the proposed universal two-stage amplifier assembly 20 which, in the simplest case, comprises two amplifier units placed on one card 22. An amplifying unit 24 of the 1st stage is preliminarily adjusted to match to a pre-selected set of averaged optical

characteristics which is designed for 2nd stage amplifying units of any of such universal assemblies, while the unit 26 of the 2nd stage is preliminarily adapted to match to a pre-selected set of averaged optical characteristics designed for 1st stage amplifier units of the universal assembly. Therefore, the 1st and the 2nd stages of the assembly 20 are in advance matched to provide a set of optical characteristics which should be better that those of one of the stages. Input 25 of the assembly is connected to input of the 1st stage, output of the 2nd stage is connected to the output 27 of the assembly, and the mid-stage of the configuration is connected to so-called mid-stage contacts 28, 29 of the assembly. It is understood that these contacts may be connected to network element(s) to be placed in the mid-stage, if so desired, or short-circuited. The assembly 20 comprises a control-communication circuit schematically marked by a dotted contour 30. The circuit 30 comprises a micro-controller 31 (which, *inter alia,* is adapted to prevent shutting down both stages of a two-stage configuration if one of the stages fails) and forms a broken control-communication channel between the 1st stage and the 2nd stage, say by providing two external contacts 32 and 33. When short-circuited, the contacts form the closed control-communication channel between the amplifiers 24 and 26.

Optionally, the contacts 28, 29 and 32, 33 may be replaced by switches (not shown) for providing any desired connections.

Fig. 3a illustrates one bi-directional configuration 40 using two unidirectional integrated assemblies 42 and 44 serving two opposite directions of transmission in a telecommunication line. Each of the assemblies 42 and 44 suits for inserting any network element (and OADM as well) in the mid stage 43 thereof. Each of the assemblies 42 and 44 can be a unidirectional assembly similar to that shown in Fig. 1b

but modified (channel 13' and CU 17') so as to prevent complete shutting down of the assembly when one of its stages is shut down.

Fig. 3b shows how the configuration 40 can be built from a pair of the identical universal assemblies 20 and 120, as illustrated in Fig. 2. For the sake of example, each of the assemblies serving a particular direction is shown with an OADM in the mid-stage. All reference numbers of the assembly 120 are formed by adding digit 1 before the analogous numerals of the assembly 20.

Fig. 3c illustrates a schematic block-diagram of a bi-directional two-stage amplifiers' configuration 50 where each direction of transmission is served by a two-stage amplifier configuration (such as 51) formed by two different integrated amplifier assemblies (cards) 52 and 54. This bi-directional configuration 50 is the most preferred one, a so-called East-West configuration, which cannot be implemented using neither the conventional two-stage integrated assembly (Fig. 1b), nor its modified version.

A so-called mid-stage 55 of both of the unidirectional configurations utilizes the real gap between inputs and outputs of the two cards 52 and 54, and may serve for inserting optical elements between the stages of the unidirectional configurations. The control-communication channels schematically shown and marked 56 and 58 are also arranged between the cards. All or some external connections can be arranged, for example, using a back-plane 57 of a shelf structure holding the cards 52, 54, fixed couplings may be formed in the back plane for the purpose.

Fig. 3d illustrates how the configuration 50 can be realized using the proposed universal integrated assembly of Fig. 2. Two assemblies 20 and 120 are shown, and their connections demonstrate how the mid-stages are formed and how new control-communication channels between the newly

formed two-stage configurations are formed using portions of the control-communication circuits of the two separate assemblies 20, 120. One of the two newly formed unidirectional configurations is shown by a dotted contour 60, its newly formed control-communication channel is marked 62. The similar configuration, with its control-communication channel, is built for the opposite direction of the optical transmission.

Though the invention has been described with the aid of schematic exemplary embodiments, it should be appreciated that other modifications and more elaborated versions of the described configurations, assembly and system might be proposed, which are to be considered part of the invention.

Claims:

1. A two-stage configuration of an optical amplifier wherein each stage of the configuration is formed by at least one optical amplifying unit, the configuration:

being adapted for inserting OADM in a mid-stage thereof,

allowing matching at least one optical characteristics of the two stages, and

being capable of leaving one of the stages to function in a regular regime whenever the other of the stages is shut down.

2. The two-stage configuration according to Claim 1, wherein each stage of the two-stage configuration is composed of one or more amplifying units matched from the point of optical characteristics, said two stages are interconnected with one another by a control-communication channel for controlling at least one parameter of the amplifying units from the following non-exhaustive list comprising gain, gain flatness and gain tilt.

3. The two-stage configuration according to Claim 1 or 2, implemented on a conventional integrated unidirectional two-stage amplifier's assembly by providing to its micro controller an ability to prevent shutting down the other one of the stages when one of the stages is to be shut down.

4. The two-stage configuration according to Claim 1 or 2, comprising its 1^{st} stage and its 2^{nd} stage located at two separate modules, wherein the optical connection and the control-communication channel between the stages is arranged externally between said modules.

5. A combined configuration comprising a pair of two-stage configurations according to claim 4, for respectively serving two opposite directions of optical transmission; in the combined configuration each of the separate modules accommodates the 1st stage of one said two-stage configuration and the 2nd stage of the other said two-stage configuration.

6. A universal integrated two-stage optical amplifier assembly, comprising a 1st stage and a 2nd stage, each formed by at least one optical amplifying unit, said 1st and 2nd stages being preliminarily matched from the point of at least one optical characteristics,

input of the assembly being connected to input of the 1st stage,

output of the 2nd stage being connected to output of the assembly,

output of the 1st stage and input of the 2nd stage are respectively connected to a pair of mid-stage contacts of the assembly (thereby allowing introducing an optical element either between the 1st stage and the 2nd stage of the universal assembly, or between any of the stages of said universal assembly and a complementary stage of another similar universal assembly,

the assembly also comprises a control-communication circuit capable of matching at least one optical characteristics of the assembly and of preventing shut down of one stage when the other is shut down , wherein said circuit being selectively configurable either to form a control-communication channel between the 1st stage and the 2nd stage of said assembly, or to disconnect said channel there-between while enabling each of the 1st stage and the 2nd stage to form a separate control-

communication channel with a complementary stage located on another similar universal assembly.

7. The assembly according to Claim 6, wherein the 1st stage and the 2nd stage are preliminarily matched so that the 1st stage of the universal assembly is preliminarily adjusted to match to a set of average characteristics designed for the 2nd stage, while the 2nd stage of the universal assembly is preliminarily adjusted to match to a set of average characteristics designed for the 1st stage, thereby any of the 1st stage and the 2nd stage of said universal assembly approximately matches to a complementary stage of said universal assembly or of another similar universal assembly.

8. The assembly according to Claim 6 or 7, wherein the control-communication circuit is capable of dynamically matching any of the 1st stage and the 2nd stage of said universal assembly to a complementary stage of said universal assembly or of another similar universal assembly.

9. The assembly according to any one of Claims 6, 7 or 8 wherein the control-communication circuit is divided into two separate portions respectively suitable for being connected to corresponding separate portions of a control-communication circuit of another similar universal assembly, so to form a control-communication channel between a 1st stage of one assembly and a 2nd stage of the other assembly and wise versa.

10. A two-stage configuration according to Claims 1 or 2, implemented using a single universal assembly according to any one of Claims 6 to 9,

the mid-stage contacts serve for connecting the stages of said universal assembly and the control-communication channel is formed between the stages of said single universal assembly.

11. A bi-directional configuration of optical amplifiers for two opposite directions of optical transmission, wherein each of the two directions of optical transmission is served by the configuration according to Claim 10.

12. A two-stage configuration according to Claim 4, implemented on two universal assemblies according to any one of Claims 6 to 9, where 1st stage of one said assembly is directly or indirectly connected to 2nd stage of the other assembly, and the control-communication channel is formed between these same stages of the different assemblies.

13. A bi-directional configuration for two opposite directions of optical transmission according to Claim 5, wherein each of the two directions of optical transmission is served by the configuration according to Claim 12.

14. A system comprising the configuration according to any one of Claims 1 to 5 and 10 to 13, further including an OADM connected in the mid stage of at least one pair of the 1st stage and 2nd stage amplifying units.

For the Applicant:

Elena Levin
Patent Attorney

ECIP/F027/IL



FIG.1A



FIG.1B



FIG.2


40
CU
13'
13'
42
17'
1st
2nd
14
16
43
CU
13'
13'
44
17'
2nd
1st
16
14
43

FIG.3A


20
32
33
CU
31
25
1st
2nd
27
24
26
28
29
OADM1
120
133
132
CU
131
127
2nd
1st
125
126
124
129
128
OADM2

FIG.3B



FIG.3C


OADM1
127
1st
132
27
2nd
128
131
133
CU
31
CU
29
129
33
28
2nd
32
1st
62
120
125
25
20
OADM2
60

FIG.3D